

MODEL: MRK 20W PLUS DRIVER					
DEFAULT WATTAGE 20W					
INPUT WATTAGE	OUTPUT CURRENT	OUTPUT VOLTAGE	SWITCH 1	SWITCH 2	SWITCH 3
8W	190MA	38V	UP	UP	UP
10W	240MA	38V	DOWN	UP	UP
14W	320MA	38V	UP	DOWN	UP
16W	370MA	38V	UP	UP	DOWN
18W	410MA	38V	DOWN	UP	DOWN
20W	470MA	38V	UP	DOWN	DOWN
22W	510MA	38V	DOWN	DOWN	DOWN

MODEL: MRK 30W PLUS DRIVER					
DEFAULT WATTAGE 30W					
INPUT WATTAGE	OUTPUT CURRENT	OUTPUT VOLTAGE	SWITCH 1	SWITCH 2	SWITCH 3
10W	230MA	38V	UP	UP	UP
16W	360MA	38V	DOWN	UP	UP
20W	440MA	38V	UP	DOWN	UP
24W	530MA	38V	UP	UP	DOWN
28W	610MA	38V	DOWN	UP	DOWN
30W	660MA	38V	UP	DOWN	DOWN
32W	730MA	38V	DOWN	DOWN	DOWN

MODEL: MRK 32W PLUS DRIVER					
DEFAULT WATTAGE 32W					
INPUT WATTAGE	OUTPUT CURRENT	OUTPUT VOLTAGE	SWITCH 1	SWITCH 2	SWITCH 3
10W	230MA	38V	UP	UP	UP
16W	360MA	38V	DOWN	UP	UP
20W	440MA	38V	UP	DOWN	UP
24W	530MA	38V	UP	UP	DOWN
28W	610MA	38V	DOWN	UP	DOWN
30W	660MA	38V	UP	DOWN	DOWN
32W	730MA	38V	DOWN	DOWN	DOWN

MODEL: MRK 40W PLUS DRIVER					
DEFAULT WATTAGE 40W					
INPUT WATTAGE	OUTPUT CURRENT	OUTPUT VOLTAGE	SWITCH 1	SWITCH 2	SWITCH 3
24W	560MA	38V	UP	UP	UP
28W	650MA	38V	DOWN	UP	UP
30W	700MA	38V	UP	DOWN	UP
32W	770MA	38V	UP	UP	DOWN
38W	840MA	38V	DOWN	UP	DOWN
40W	880MA	38V	UP	DOWN	DOWN
42W	940MA	38V	DOWN	DOWN	DOWN

MODEL: MRK 50W PLUS DRIVER					
DEFAULT WATTAGE 50W					
INPUT WATTAGE	OUTPUT CURRENT	OUTPUT VOLTAGE	SWITCH 1	SWITCH 2	SWITCH 3
25W	580MA	38V	UP	UP	UP
30W	710MA	38V	DOWN	UP	UP
38W	880MA	38V	UP	DOWN	UP
40W	910MA	38V	UP	UP	DOWN
45W	990MA	38V	DOWN	UP	DOWN
50W	1100MA	38V	UP	DOWN	DOWN
52W	1160MA	38V	DOWN	DOWN	DOWN

MODEL: MRK 60W PLUS DRIVER					
DEFAULT WATTAGE 60W					
INPUT WATTAGE	OUTPUT CURRENT	OUTPUT VOLTAGE	SWITCH 1	SWITCH 2	SWITCH 3
40W	920MA	38V	UP	UP	UP
45W	1020MA	38V	DOWN	UP	UP
50W	1120MA	38V	UP	DOWN	UP
55W	1230MA	38V	UP	UP	DOWN
57W	1290MA	38V	DOWN	UP	DOWN
60W	1360MA	38V	UP	DOWN	DOWN
62W	1410MA	38V	DOWN	DOWN	DOWN

MODEL: MRK 100W PLUS DRIVER					
DEFAULT WATTAGE 100W					
INPUT WATTAGE	OUTPUT CURRENT	OUTPUT VOLTAGE	SWITCH 1	SWITCH 2	SWITCH 3
65W	1520MA	38V	UP	UP	UP
70W	1630MA	38V	DOWN	UP	UP
75W	1740MA	38V	UP	DOWN	UP
80W	1850MA	38V	DOWN	DOWN	UP
85W	1940MA	38V	UP	UP	DOWN
90W	2050MA	38V	DOWN	UP	DOWN
95W	2150MA	38V	UP	DOWN	DOWN
100W	2250MA	38V	DOWN	DOWN	DOWN